



# OFDC-B8

## Outdoor fiber distribution closure

The gel sealed outdoor distribution closure is used to break out fibers from a looped cable to connect business customers, MDU's or single living units.

The gel, used for both, closure and cable seals, allows easy access and is fully re-useable.

### Features

- Single ended design
- Compact enclosure (163 x 326 x 102 mm)
- Gel block with spring loading for the cable seal
- Not required to cut loop-through fiber of the feeding cable
- Organizer can be removed from closure body
- Compatible with RECORDsplice, SMOUV and ANT splice protectors
- Transient free customer provisioning
- Drop cables are terminated individually
- Separate storage of un-connected fibers from spliced drop fibers
- Possibility to integrate PON splitters
- Main cable up to 18 mm diameter  
Drop cable up to 6 mm diameter
- Easy drop cable termination on strain relief device.
- The closure can be used as well in aerial, pedestal and underground (up to 2 meters) environment

## Kit content

- Box with fiber organizer
- Main cable seal and termination device
- Drop cable seal for 8 drops with drop cable termination devices

## Ordering Information

### Xpres version

**OFDC-B8- XXX / X - X - XX**

**LX1** Xpress-drop LC/UPC  
**LX2** Xpress-drop LC/APC 8°  
**SX1** Xpress-drop SC/UPC  
**SX2** Xpress-drop SC/APC

Number of adapters and pigtails included (**2, 4 or 8**)

**U** Universal splice holder  
(12 splices RECORDsplice & SMOUV or a combination)

**NN** no splitter  
**14** 1:4 splitter  
**18** 1:8 splitter

### ISROD version

**OFDC-B8- XXX - X - XX - X**

**U12** Splice tray with universal holder for 12 splices  
**S36** Splice tray for 36 splices with SMOUV

Number of trays (**1 or 2**)

**NN** no splitter  
**14** 1:4 splitter  
**18** 1:8 splitter  
**1G** 1:16 splitter

Number of ISROD included (**2, 4 or 8**)

### Adapters

OC-ADP-X1-X1-NNCS-(24) XPRESS-DROP LC/UPC (MOQ = 24 pcs)  
OC-ADP-X2-X2-NNCS-(24) XPRESS-DROP LC/APC 8° (MOQ = 24 pcs)  
OFDC-ISROD-6MM-(24) (MOQ/SPQ = 24 pcs)

### Ordering example

24 x OC-ADP-X1-X1-NNCS-(24) 1 bag with 24 pcs

**For more technical options and order quantity information, please consult the products ordering guides or your local sales representative.**

RECORDsplice, SMOUV, TE (logo) and TE Connectivity are trademarks of the TE Connectivity group of companies and its licensors.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

Tyco Electronics Raychem bvba  
Diestsesteenweg 692  
3010 Kessel-Lo, Belgium  
Tel 32-16 351 011 (USA)1-919-557-8900  
Fax 32-16 351 697 (USA)1-919-557-8498  
www.te.com  
www.telecomnetworks.com  
TC 1045/DS/6 03/12

